

Coaxial cable

FABER[®] Sat 75 Ohm 0,7/2,9 Digital



DERZEIT KEIN BILD VERFÜGBAR. | NO IMAGE AVAILABLE.

Application: For the connection of satellite-TV or BC-TV components.

Construction and technical data:

CPR-performance:	on request
Sheathing material:	PVC
Permitted outer cable temperature, fixed, °C:	-5 - +70 °C
Bending radius, fixed installation:	10 x Ø
Impedance:	75 Ohm

The products and information presented here are for technical calculation only. They are subject to technical progress and in no way represent the ability of shipment. Outer diameters are approximately.

Attenuation at 20 °C

f (MHz)	D (dB/100 m)
100	8.8
300	16.5
450	21.2
862	28.2
1000	31.0
1350	36.9
1750	42.5
2050	46.3
2500	53.6

FABER[®] SAT 0,7/2,9

inner conductor material:	copper, solid, bare
Inner conductor diameter, mm:	0.7 mm
Insulation:	foam-PE
Outer screen:	aluminium foil + tinned copper braid
Sheathing material:	PVC
Suitable for HD/digital:	yes
Minimum bending radius:	10 x Ø
Operating temperature:	-5 - +70 °C
Impedance, ohm:	75 Ohm
Screening efficiency:	90 dB
DC-resistance inner conductor:	52 Ohm/km
DC-resistance outer screen:	42 Ohm/km

part no.	part name	Ø [mm]	Cu [kg/km]	G [kg/km]
100485	FABER® SAT 0,7/2,9 DIGITAL 75 Ohm WS	4.5	12,5	29

Ø | outer diameter approx.

Cu | Copper weight (GER)

G | net weight